User Guide for FW Upgrade Tool on Windows

1. Open UpgradeFW_ST7S1031_v2.00_20180118.exe with administrator privilege and click "Yes" if asked to allow program from unknown publisher make changes to this computer.

	<u>O</u> pen					-	D
•	Run as <u>a</u> dministrator						
	Troubleshoot compatibility		pgradeFW_ST7S1031_v2.00_Windows	ٽ ~	Sea	arch UpgradeFW_	ST7S1031
	<u>P</u> in to Start		ime	Date modified		Туре	Si
	7-Zip	>	UpgradeFW ST7S1031 v2.00.exe	1/18/2018 1:48	AM	Application	
	CRC SHA	>					

2. Check the box of all drives that you want to upgrade, click "rescan" icon if you don't see target drive shown up. This program only upgrades from drives with ST7S1030 firmware.



3. Click "Upgrade Firmware" icon and wait for few seconds until "Pass" popped up at upper right corner.

🦧 Seagate Firmware Upgrade Tool(V2.00)_20180118						
	GATE					
Device						
🔍 rescan						
🔽 Seagate Nytro 141 X	Seagate Nytro 141 XA512DC10001 ST7S1030 7GC0021q					
Feature	Message					
Firmware Ver. ST7S1031	DownLoedMicroCode_15 OK. DownLoedMicroCode_16 OK. DownLoedMicroCode_17 OK. DownLoedMicroCode_18 OK.	^				
Function	DownLoadMicroCode_19 OK. DownLoadMicroCode_20 OK					
	DownLoadMicroCode_21 OK.					
	DownLoadMicroCode_22 OK.					
Upgrade Firmware	DownLoadMicroCode_25 OK.					
	DownLoadMicroCode_remainder OK.					
	DownLoadMicroCode-lasted OK. Device 01 DownLoadMicroCode OK					
	Local of Download Control of Children Control of Children	~				

4. Click "rescan" icon again to confirm if firmware version changed to "ST7S1031",



5. Firmware Upgrade is completed successfully.